
How to disable CLKOUT output in Deep sleep mode?

Questions:

How to disable CLKOUT output in Deep sleep mode?

Answer:

For some AT32F4xx series, CLKOUT output cannot be disabled automatically in Deep sleep mode.

The solution is to disable CLKOUT output through software before Deep sleep mode entry and then configure CLKOUT after waking up from Deep sleep mode. Typical code is as follows:

```
static void clkout_config(void)
{
    gpio_init_type gpio_init_struct;
    /* enable/disable gpio port clock */
    crm_periph_clock_enable(CRM_GPIOA_PERIPH_CLOCK, TRUE);
    /* set default parameter */
    gpio_default_para_init(&gpio_init_struct);
    /* clkout gpio init */
    gpio_init_struct.gpio_drive_strength = GPIO_DRIVE_STRENGTH_STRONGER;
    gpio_init_struct.gpio_mode = GPIO_MODE_MUX;
    gpio_init_struct.gpio_pins = GPIO_PINS_8;
    gpio_init_struct.gpio_pull = GPIO_PULL_NONE;
    gpio_init(GPIOA, &gpio_init_struct);
    /* config clkout division */
    crm_clkout_div_set(CRM_CLKOUT_DIV_1);
    /* config clkout clock */
    crm_clock_out_set(CRM_CLKOUT_PLL_DIV_4);
}
```

Type: MCU applications

Applicable products: ATF32F403, AT32F413, AT32F415, ATF32F403A, ATF32F407

Main function: PWC

Minor function: CLKOUT

Document revision history

Date	Revision	Changes
2022.3.10	2.0.0	Initial release

IMPORTANT NOTICE – PLEASE READ CAREFULLY

Purchasers are solely responsible for the selection and use of ARTERY's products and services, and ARTERY assumes no liability whatsoever relating to the choice, selection or use of the ARTERY products and services described herein.

No license, express or implied, to any intellectual property rights is granted under this document. If any part of this document deals with any third party products or services, it shall not be deemed a license grant by ARTERY for the use of such third party products or services, or any intellectual property contained therein, or considered as a warranty regarding the use in any manner whatsoever of such third party products or services or any intellectual property contained therein.

Unless otherwise specified in ARTERY's terms and conditions of sale, ARTERY provides no warranties, express or implied, regarding the use and/or sale of ARTERY products, including but not limited to any implied warranties of merchantability, fitness for a particular purpose (and their equivalents under the laws of any jurisdiction), or infringement of any patent, copyright or other intellectual property right.

Purchasers hereby agrees that ARTERY's products are not designed or authorized for use in: (A) any application with special requirements of safety such as life support and active implantable device, or system with functional safety requirements; (B) any air craft application; (C) any automotive application or environment; (D) any space application or environment, and/or (E) any weapon application. Purchasers' unauthorized use of them in the aforementioned applications, even if with a written notice, is solely at purchasers' risk, and is solely responsible for meeting all legal and regulatory requirement in such use.

Resale of ARTERY products with provisions different from the statements and/or technical features stated in this document shall immediately void any warranty grant by ARTERY for ARTERY products or services described herein and shall not create or expand in any manner whatsoever, any liability of ARTERY.